



## E3Z-L81-IL3 5M

Датчик фотоэл. прямоуг. E3Z, диффузный, красный свет, 90+/-30мм, узкий луч, PNP, кабель 5м, IO-link COM 3

# Технические характеристики

<b>Shape</b>	Cuboid
<b>Sensing method</b>	Diffuse reflective
<b>Sensing distance</b>	90 mm
<b>Sensing distance (min.)</b>	60 mm
<b>Setting method</b>	IO-Link, Manual adjustment
<b>Connection method</b>	Cable
<b>Cable length</b>	5 m
<b>Output type</b>	IO-Link, PNP
<b>Operation mode</b>	Dark-ON, Light-ON
<b>IO-Link baud rate</b>	COM3 (230.4 kbps)
<b>Response time</b>	1 ms
<b>Material housing</b>	PBT
<b>Thread size</b>	Other
<b>Width</b>	10.8 mm
<b>Height</b>	31 mm
<b>Depth</b>	20 mm
<b>Type of light</b>	Polarity free red light
<b>Spot size</b>	2.5 mm
<b>Power supply voltage</b>	10-30 V
<b>Features</b>	Narrow beam
<b>Degree of protection (IP)</b>	IP67

## Дополнительные принадлежности



**E39-L104**

Mounting bracket for E3Z sensor, standard, vertical mounting



**E39-L142**

Mounting Bracket, protective side wall (for E3Z)



**E39-L144**

Sensor mounting Bracket, Protective bracket for E3Z pre-wired



**E39-L150**

Sensor mounting Bracket for E3Z, 100mm high post



**E39-L151**

Sensor mounting Bracket, for E3Z, 200mm high post



**E39-L153**

Mounting bracket for E3Z sensor, L shape, for prewired



**E39-L43**

Mounting bracket for E3Z sensor, side mounting



**E39-L44**

Mounting bracket for E3Z sensor, rear mounting



**E39-L98**

Protective metal cover for E3S-A/E3Z vertical sensor

Библиотека дву-  
/трехмерных CAD  
рисунков



## CJ-series -[EtherNet/IP]- NX-EIC + NX-ILM400 - [IO-Link]- E3Z-series Photoelectric Sensor

Руководство по  
подключению

EN PDF 3,3 МБ



## E3Z IO-Link Инструкция

EN PDF 2,7 МБ



## IO-Link System Руководство пользователя

EN PDF 11,1 МБ



## Sysmac: A Fully Integrated Platform Брошюра

EN PDF 10,4 МБ



## E3Z Брошюра

RU PDF 1,3 МБ



## E3Z IO-Link Datasheet Спецификация

EN PDF 4,5 МБ



## NJ-series -[EtherCAT]- GX-ILMxxx -[IO-Link]- E3Z-series Photoelectric Sensor

Руководство по  
подключению

EN PDF 2,2 МБ



## Кабели и разъемы для датчиков Брошюра

RU PDF 5,9 МБ



## E3Z Файл IO-Link IODD

EN ZIP 813,5 КБ



## IO-Link Series Брошюра

RU PDF 6,2 МБ



## NJ-series -[EtherCAT]- NX-ECC + NX-ILM400 - [IO-Link]- E3Z-series Photoelectric Sensor

Руководство по  
подключению

EN PDF 2,5 МБ