



E6C2-CWZ1X 1000P/R 5M

Энкодер инкрементальный

Технические характеристики

Model	Incremental encoder
Construction size	50 mm
Pulses per rotation	1000
Signal outputs	A, B, Z
Shaft diameter	6 mm
Power supply voltage	4.8-5.2 V
Output type	Line driver (RS-422)
Connection method	Cable
Cable length	5 m

Дополнительные принадлежности



E69-C06B

Accessory encoder, shaft coupling for E6B2/E6C2-C/E6CP/E6D encoder



E69-C06M

Accessory encoder, shaft coupling dia. 6mm, metal



E69-C68B

Accessory encoder, shaft coupling dia. 6mm and 8mm



E69-FCA

Flange for E6C2-C encoder

Библиотека дву-
/трехмерных CAD
рисунков



E6C2-C Incremental Rotary Encoder

Спецификация

EN PDF 888,4 КБ